

ENCLOSED ELECTRONIC

Transformers

WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

PRODUCT DESCRIPTION

SMART Electronic Transformers, available from 60 to 300 watts, incorporate trouble-shooting diagnostics, full scale dimming and a compact size with auto reset, soft start and short circuit protection technologies.

FEATURES

- 1W minimum load
- Use for all initial installations to ensure safe and primary side connections in a wiring compartment
- Dimming with Electronic Low Voltage dimmers

SPECIFICATIONS

Construction: Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.

Output: 12V, 24V

Frequency: 20khz

Details: In the case of a system overload or short circuit the transformer will revert to a "hold" position and then automatically reset the system when the problem is solved. System protection is designed to last several hours.

Standards: UL Listed

ORDER NUMBER

| Model | Output | L | W | H |
|-----------------|---------------|---------------------------------|---------------------------------|---------------------------------|
| EN-1260-RB-AR | 12V, 1 x 60W | 6 ⁵ / ₈ " | 1 ⁵ / ₈ " | 1 ¹ / ₈ " |
| EN-1275-RB-AR | 12V, 1 x 75W | 6 ⁵ / ₈ " | 1 ⁵ / ₈ " | 1 ¹ / ₈ " |
| EN-12100-RB-AR | 12V, 1 x 100W | 6 ¹ / ₄ " | 3" | 1 ³ / ₄ " |
| EN-12150-RB-AR | 12V, 1 x 150W | 6 ¹ / ₄ " | 3" | 1 ³ / ₄ " |
| EN-24150-RB-AR* | 24V, 1 x 150W | 6 ¹ / ₂ " | 3" | 1 ⁵ / ₈ " |
| EN-B12PY-AR* | 12V, 1 x 250W | 6 ¹ / ₂ " | 3 ³ / ₈ " | 2 ¹ / ₂ " |
| EN-B24PZ-AR* | 24V, 1 x 300W | 6 ¹ / ₂ " | 3 ³ / ₈ " | 2 ¹ / ₂ " |

*Includes LED indicator lights and integral push-in terminals

ACCESSORIES

Multiple Terminal Block

Accommodates up to 6 output connections for 14 AWG wires. Terminal block is used to easily wire together multiple output connections for a neat under cabinet installation without the use of open splices. Perfect for wiring up to 3 button lights at 20W or 6 button lights at 10W.

| Model | L | W | H |
|--------|---------------------------------|---------------------------------|---------------------------------|
| MTB-01 | 3 ³ / ₄ " | 1 ³ / ₄ " | 7 ¹ / ₈ " |

EN- _ - -

Example: EN-12100-RB-AR

wacighting.com

Phone (800) 526.2588

Fax (800) 526.2585

Headquarters/Eastern Distribution Center

44 Harbor Park Drive

Port Washington, NY 11050

Central Distribution Center

1600 Distribution Ct

Lithia Springs, GA 30122

Western Distribution Center

1750 Archibald Avenue

Ontario, CA 91760