
# WAC LIGHTING

Responsible Lighting<sup>®</sup>

44 Harbor Park Drive Port Washington, NY 11050 Tel: 800.526.2588 www.waclighting.com

### COUNTERBALANCE ADJUSTABLE CHANDELIER





Ordering Matrix		
Model	Series	Finish
AP	7RE	BN

Ordering Example (model number - series number - finish): AP-7RE-BN

#### **Product Details Description:** BALANS series low voltage adjustable pendant with white glass shades. Designed for flat ceilings. • Materials: Formed metal canopy, counterbalance, decorative pendant bar, and j-box cover plate. Galvanized steel backplate. One low voltage electronic transformer located in the canopy. Two sets of low voltage wires running from the canopy to the deco bar. Seven cased white glass shades. Mounting hardware, including screws and wire nuts are included. Transformer: One 12v electronic low voltage (model EN-12150-R-AR). 120 volt input / 12 volt output. 50hz/60hz. Lamping: Seven 20w xenon bi-pin BP-20 included. Maximum wattage for each lamp socket is 20 watts. Mounting: Mounts over a standard 4" junction box. Base plate covers junction box opening, the canopy attaches to base plate with three screws. There are two trade sized knockout on the base plate. Finish: Brushed Nickel (BN) Listing: U.L. & C.U.L. listed. 5 year WAC Lighting product warranty.

#### **Specification Features**

Electronic transformer has advanced auto-reset, soft start and short circuit protection features. The soft start delayed lamp start feature extends lamp life by delaying the abrupt inrush current to the lamp.

The j-box cover plate may be field painted by the installer to match the color of the ceiling.

- "Quick-Ship" item, always in stock and available for immediate shipment.
- Dim the AP-7RE pendant with an electronic low voltage dimmer.

WAC Lighting reserves the right to modify the design of our products as part of the company's continuous improvement program.

## **MODEL AP-7RE**