


615 South Street Garden City, NY 11530 Tel:516-515-5000 Fax:516-515-5050 www.waclighting.com

CATALOG NUMBER	<u>TYPE</u>
PROJECT	

12V MAGNETIC TRANSFORMER

MODEL SRT-500M-12V





Ordering Matrix		
Model	Finish	Accessories
SRT-500M-12V	BK	See table below

Ordering Example (model-finish): SRT-500M-12V

Product Details

Description: Short Circuit Protection. Thermal Protection. Boost Top Option

250 watt for per circuit . Suitable for damp locations

Catalog Number: 500M = 500 watt ; M = Magnetic

12V = 12 Volt

Input: 120V (60Hz)

Output: 12V Per Circuit

Max Load: 500W (2 x 250W circuit)

Max Input Amp: 4.2A (@ 120V)

Transformer 60 Hz

Frequency:

Dimming: Dimmable with magnetic dimmers. Dimmers should always be

installed on the primary side of the transformer.

Listing: U.L. listed, File Number E223916.

Specification Features

- Wiring: Knock out holes on both sides, for convenient wiring. Input lead wire length is 6". Output screw terminals for tight wire connections.
- Dimming: Use magnetic low volt dimmers. Dimmers are installed on primary wiring side.
- Protection: Automatic resetting thermal protector on the primary side. Magnetic transformers feature "push to reset" circuit breakers.
- **5 year** WAC Lighting product warranty.